



DB150 Standard Pinout

Always identify proper wiring via continuity check & color when using multi-strand cables.

The calibration certificate for the device should be used as the definitive reference for custom wiring options.



PIN	DB150 CONTROLLER
1	Ground: Common ground for power, digital communications, analog signals and alarms.
2	NC: This pin is not connected to the device by default. <i>Optional: 4–20 mA analog output signal</i>
3	Ground: Common ground for power, digital communications, analog signals and alarms.
4	Analog Out: 0–5 Vdc output signal. <i>Optional: 1–5 Vdc, 0–10 Vdc, 4–20 mA</i>
5	Power In: Powers the device, see the specification sheet for details.
6	NC: This pin is not connected to the device.
7	Analog In: 0–5 Vdc analog DC input defining the setpoint. <i>Optional: 1–5 Vdc, 0–10 Vdc, or 4–20 mA</i>
8	NC: This pin is not connected to the device.
9	Ground: Common ground for power, digital communications, analog signals and alarms.
10	Ground: Common ground for power, digital communications, analog signals and alarms.
11	Analog Out 2: Static 5.12 Vdc. <i>Optional: Analog signal to indicate another parameter (0–5 Vdc, 1–5 Vdc, 0–10 Vdc, or 4–20 mA)</i>
12	NC: This pin is not connected to the device.
13	NC: This pin is not connected to the device.
14	Rx or B (+): Receives RS-232 (Rx) or RS-485 B (+) signals to change the device's settings.
15	Tx or A (–): Sends RS-232 (Tx) or RS-485 A (–) signals from the device.

PIN	DB150 METER
1	Ground: Common ground for power, digital communications, analog signals and alarms.
2	NC: This pin is not connected to the device by default. <i>Optional: 4–20 mA analog output signal</i>
3	Ground: Common ground for power, digital communications, analog signals and alarms.
4	Analog Out: 0–5 Vdc output signal. <i>Optional: 1–5 Vdc, 0–10 Vdc, 4–20 mA</i>
5	Power In: Powers the device, see the specification sheet for details.
6	NC: This pin is not connected to the device.
7	Ground to Tare: Ground this pin to tare the device.
8	NC: This pin is not connected to the device.
9	Ground: Common ground for power, digital communications, analog signals and alarms.
10	Ground: Common ground for power, digital communications, analog signals and alarms.
11	Analog Out 2: Static 5.12 Vdc. <i>Optional: Analog signal to indicate another parameter (0–5 Vdc, 1–5 Vdc, 0–10 Vdc, or 4–20 mA)</i>
12	NC: This pin is not connected to the device.
13	NC: This pin is not connected to the device.
14	Rx or B (+): Receives RS-232 (Rx) or RS-485 B (+) signals to change the device's settings.
15	Tx or A (–): Sends RS-232 (Tx) or RS-485 A (–) signals from the device.

Note: Do not connect RS-485 to RS-232 units or cables. Damage will occur. Check part number or contact factory to verify RS-485 functionality.